

NASA TECH BRIEF

NASA Pasadena Office



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

A Nonlinear-Coherence Receiver

Mathematical analysis and detailed study of a generic model for a coherent receiver has demonstrated that the nonlinear coherence between a given biphasemodulated input signal and a supplied reference signal can be used advantageously in present-day receivers to improve telecommunication systems. There are many special cases of the general structure, but the only two that have been explored thus far (the data-aided and hybrid carrier tracking loops) have provided significant improvement in performance over the present-day phase-coherent tracking, telemetry, and command systems which utilize PCM/PSK/PM modulation.

The usual method for examining the mutual power between two signals at an arbitrary frequency is through the use of a cross-spectrum, that is, the spectral density of power that is mutually shared in a phase-coherent manner. It is important to note that each signal can have power in a common frequency band without there being cross-spectral power in that band; the existence of common frequency-components does not imply mutually coherent power.

In a nonlinear system, it is possible to have coherence between a signal at one frequency and another signal at some multiple of that frequency. For example, when the generic model includes a squaring loop, an input signal with energy centered at a nominal frequency is squared (nonlinear operation) to produce a signal that is centered at twice the nominal frequency and is phase-coherent with the suppressed carrier signal. The signal at the higher frequency is tracked by a conventional phase-lock loop with an oscillator of the same nominal frequency.

The results of detailed mathematical analyses of the generic model also demonstrate that nonlinear coherence receivers operated in a multiple loop configuration can very readily be made to provide improved signal-to-noise figures inasmuch as phase-time relationships within desired signals are not common with noise signals. Moreover, with telemetry signals which can have constant phase errors over several symbol intervals, appropriate delay elements can be introduced into the generic model in order to exploit sideband power in much the same manner as is done in differentially coherent detection or time diversity reception; mathematical expressions for the signal and noise components of voltages appearing at various points in the generic model are tabulated in the report which summarizes the results of the study.

Note:

Requests for further information may be directed to:

Technology Utilization Officer
NASA Pasadena Office
4800 Oak Grove Drive
Pasadena, California 91103
Reference: TSP 73-10144

Source: Marvin K. Simon of
Caltech/JPL
and William C. Lindsey of
University of Southern California
under contract to
NASA Pasadena Office
(NPO-11921)

Category 02